



# Phoenix Audio Stingray Module Setup Guide

**About:**

The MT700 – Stingray Distributed Array Mixer from Phoenix Audio Technologies is an all-in-one smart mixer that responds to rapidly evolving communication trends, conference environments, and connectivity technologies. Used on its own or in tandem with video, the MT700 – Stingray Mixer offers a simple solution to the complex requirements of today's professional conferencing spaces.

**Setup Communication:**

The Stingray is controlled over TCP-IP on port 8888. In Compass Navigator, please insert the IP address under Device Properties. The Stingray unit only accepts one host connection at a time. Please use one Compass Controller for controlling one Stingray unit.

**Setup Login:**

In Compass Navigator on the Stingray's device properties tab, enter the unit's MAC address under "Login". If the unit is password protected, then enter the password under "Password". The login type is type "Common". These credentials are required for control.

**Setup Complete**

Upload and update the project for use.

**Compass Control® Pro Offers:****Bi-Directional Feedback:**

- Audio Conferencing Control
  - Dialer
  - Phonebook
  - Call History
- Audio Controls
  - Input Muting
  - Output Muting
  - Speaker Volume Control
- Multi-Room Control
  - Room Splitting
  - Room Combining